



The Inovonics EN1223D double-button water-resistant pendant is our smallest, lightest and most versatile pendant, designed to meet the specific protection needs of patrolling guards, bank employees and retail store employees.

Product Features

Can be worn in the shower, bathtub or rain

Double-button activation reduces false alarms

Neck cord and belt clip included for easy conversion

LED dimmed to minimize observation of alarm activation

Fully supervised to help ensure reliability

Weighs less than 1.3oz (40gm)

UL listed

Product Specifications

Dimensions: 2.2" x 1.9" x 0.72" (5.6 cm x 4.8 cm x 1.8 cm)

Weight: 1.3 oz (37 g)

Typical battery life: 1-2 years

Internal battery type: Panasonic CR2450

Accessories: ACC603M metal necklace, ACC603P plastic necklace, ACC623B water-resistant pendant black accessory pack, ACC623L/S water-resistant pendant wrist strap

Operating environment:

Temperature: 32°F to 140°F (0°C to 60°C); 32°F to 120°F (0°C to 49°C) for UL installations

Environment: Water resistant, non-submersible

Market: North America, Australia, New Zealand

EchoStream® frequency: 902-928 MHz, frequency hopping spread spectrum

Check-in time frequency: 3 minutes

Regulatory compliance: FCC, RoHS, IP54 Dust and Water Resistance (IEC 60529), UL 1023, ULC/ORD-C1023-74

Reference Materials (available at www.inovonics.com)

EN1223D EchoStream® Double-Button Water-Resistant Pendant Transmitter
Installation and Operation Manual

EchoStream Developer Guide

EchoStream One-Way Security Developer Guide

Inovonics Product Catalog: North America

- The range and performance of any wireless product depends on the structure and environment in which it operates.
- Continual enhancements to our products may cause specifications to change without notice.
- Patents: 7,154,866; 7,554,932; 7,746,804; others pending.
- Inovonics supports recycling and reuse whenever possible. Please recycle these parts using a certified electronics recycler.

Technical documents

For technical documents visit us at <http://www.inovonics.com/support/tech-documents/> or use the QR code below.

